

Self-aligning ball bearings: size chart

Searchable nominal dimensions from verified catalogue records

796 dimension rows | 796 distinct model records | FAG, KOYO, NSK, SKF

Use the table

Choose the correct construction section, then use the PDF search for the complete designation. Compare the brand and all suffixes. Rows are ordered by inside, outside and axial dimensions, then brand and designation. Click a designation to open its existing BearingScope product record.

Read the symbols, not just three numbers

All numeric table entries are in millimetres. Preserve the printed symbol: an inner-ring bore, a roller-complement diameter, ring width and complete assembly height are different quantities. Section notes identify special construction and seat conditions.

Limits of this reference

This is an original BearingScope compilation, not a manufacturer manual, full technical datasheet, engineering drawing, CAD file or exhaustive standard-size schedule. Complete source-labelled dimension triples are included; incomplete or conflicting records are withheld. Equal nominal dimensions do not prove fit, performance, suffix equivalence or safe interchange.

Technical basis and data date

Values are retained manufacturer-catalogue facts from the matching FAG, KOYO, NSK, SKF records. Product captures predate this edition; reviewed source snapshots were assembled on 2-3 October 2026. Each linked model record identifies its manufacturer. Primary-source addresses, collection dates and dimension-property evidence are retained privately. Explanations and layout are original; no installation limits, vehicle fitment, load ratings or tolerances are inferred.

Sections in this download

Self-aligning ball bearings - 796 rows - page 2

Self-aligning ball bearings

Self-aligns ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
FAG	135-TVH	d = 5	D = 19	B = 6	Self-aligning ball bearing
NSK	135	d = 5	D = 19	B = 6	Self-aligning ball bearing
SKF	135 TN9	d = 5	D = 19	B = 6	Self-aligning ball bearing
FAG	126-TVH	d = 6	D = 19	B = 6	Self-aligning ball bearing
NSK	126	d = 6	D = 19	B = 6	Self-aligning ball bearing
SKF	126 TN9	d = 6	D = 19	B = 6	Self-aligning ball bearing
FAG	127-TVH	d = 7	D = 22	B = 7	Self-aligning ball bearing
NSK	127	d = 7	D = 22	B = 7	Self-aligning ball bearing
SKF	127 TN9	d = 7	D = 22	B = 7	Self-aligning ball bearing
FAG	108-TVH	d = 8	D = 22	B = 7	Self-aligning ball bearing
NSK	108	d = 8	D = 22	B = 7	Self-aligning ball bearing
SKF	108 TN9	d = 8	D = 22	B = 7	Self-aligning ball bearing
FAG	129-TVH	d = 9	D = 26	B = 8	Self-aligning ball bearing
NSK	129	d = 9	D = 26	B = 8	Self-aligning ball bearing
SKF	129 TN9	d = 9	D = 26	B = 8	Self-aligning ball bearing
FAG	1200-TVH	d = 10	D = 30	B = 9	Self-aligning ball bearing
FAG	1200-TVH-C3	d = 10	D = 30	B = 9	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
KOYO	1200	d = 10	D = 30	B = 9	Self-aligning ball bearing
NSK	1200	d = 10	D = 30	B = 9	Self-aligning ball bearing
SKF	1200 ETN9	d = 10	D = 30	B = 9	Self-aligning ball bearing
FAG	2200-2RS-TVH	d = 10	D = 30	B = 14	Self-aligning ball bearing
FAG	2200-TVH	d = 10	D = 30	B = 14	Self-aligning ball bearing
FAG	2200-TVH-C3	d = 10	D = 30	B = 14	Self-aligning ball bearing
KOYO	2200	d = 10	D = 30	B = 14	Self-aligning ball bearing
KOYO	22002RS	d = 10	D = 30	B = 14	Self-aligning ball bearing
NSK	2200	d = 10	D = 30	B = 14	Self-aligning ball bearing
SKF	2200 E-2RS1TN9	d = 10	D = 30	B = 14	Self-aligning ball bearing with seals on both sides
SKF	2200 ETN9	d = 10	D = 30	B = 14	Self-aligning ball bearing
NSK	1300	d = 10	D = 35	B = 11	Self-aligning ball bearing
NSK	2300	d = 10	D = 35	B = 17	Self-aligning ball bearing
FAG	1201-TVH	d = 12	D = 32	B = 10	Self-aligning ball bearing
FAG	1201-TVH-C3	d = 12	D = 32	B = 10	Self-aligning ball bearing
FAG	1201-TVH-C3>N	d = 12	D = 32	B = 10	Self-aligning ball bearing
FAG	1201-TVH>N	d = 12	D = 32	B = 10	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
KOYO	1201	d = 12	D = 32	B = 10	Self-aligning ball bearing
NSK	1201	d = 12	D = 32	B = 10	Self-aligning ball bearing
SKF	1201 ETN9	d = 12	D = 32	B = 10	Self-aligning ball bearing
FAG	2201-2RS-TVH	d = 12	D = 32	B = 14	Self-aligning ball bearing
FAG	2201-2RS-TVH>N	d = 12	D = 32	B = 14	Self-aligning ball bearing
FAG	2201-TVH	d = 12	D = 32	B = 14	Self-aligning ball bearing
FAG	2201-TVH-C3	d = 12	D = 32	B = 14	Self-aligning ball bearing
FAG	2201-TVH-C3>N	d = 12	D = 32	B = 14	Self-aligning ball bearing
FAG	2201-TVH>N	d = 12	D = 32	B = 14	Self-aligning ball bearing
KOYO	2201	d = 12	D = 32	B = 14	Self-aligning ball bearing
KOYO	22012RS	d = 12	D = 32	B = 14	Self-aligning ball bearing
NSK	2201	d = 12	D = 32	B = 14	Self-aligning ball bearing
SKF	2201 E-2RS1TN9	d = 12	D = 32	B = 14	Self-aligning ball bearing with seals on both sides
SKF	2201 ETN9	d = 12	D = 32	B = 14	Self-aligning ball bearing
FAG	1301-TVH	d = 12	D = 37	B = 12	Self-aligning ball bearing
NSK	1301	d = 12	D = 37	B = 12	Self-aligning ball bearing
SKF	1301 EM	d = 12	D = 37	B = 12	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
SKF	1301 ETN9	d = 12	D = 37	B = 12	Self-aligning ball bearing
NSK	2301	d = 12	D = 37	B = 17	Self-aligning ball bearing
SKF	2301	d = 12	D = 37	B = 17	Self-aligning ball bearing
FAG	1202-TVH	d = 15	D = 35	B = 11	Self-aligning ball bearing
FAG	1202-TVH-C3	d = 15	D = 35	B = 11	Self-aligning ball bearing
FAG	1202-TVH-C3>N	d = 15	D = 35	B = 11	Self-aligning ball bearing
FAG	1202-TVH>N	d = 15	D = 35	B = 11	Self-aligning ball bearing
KOYO	1202	d = 15	D = 35	B = 11	Self-aligning ball bearing
NSK	1202	d = 15	D = 35	B = 11	Self-aligning ball bearing
SKF	1202 ETN9	d = 15	D = 35	B = 11	Self-aligning ball bearing
FAG	2202-2RS-TVH	d = 15	D = 35	B = 14	Self-aligning ball bearing
FAG	2202-2RS-TVH-C3	d = 15	D = 35	B = 14	Self-aligning ball bearing
FAG	2202-2RS-TVH-C3>N	d = 15	D = 35	B = 14	Self-aligning ball bearing
FAG	2202-2RS-TVH>N	d = 15	D = 35	B = 14	Self-aligning ball bearing
FAG	2202-TVH	d = 15	D = 35	B = 14	Self-aligning ball bearing
FAG	2202-TVH-C3	d = 15	D = 35	B = 14	Self-aligning ball bearing
FAG	2202-TVH-C3>N	d = 15	D = 35	B = 14	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
FAG	2202-TVH>N	d = 15	D = 35	B = 14	Self-aligning ball bearing
KOYO	2202	d = 15	D = 35	B = 14	Self-aligning ball bearing
KOYO	22022RS	d = 15	D = 35	B = 14	Self-aligning ball bearing
NSK	2202	d = 15	D = 35	B = 14	Self-aligning ball bearing
SKF	2202 E-2RS1TN9	d = 15	D = 35	B = 14	Self-aligning ball bearing with seals on both sides
SKF	2202 ETN9	d = 15	D = 35	B = 14	Self-aligning ball bearing
KOYO	1302	d = 15	D = 42	B = 13	Self-aligning ball bearing
NSK	1302	d = 15	D = 42	B = 13	Self-aligning ball bearing
SKF	1302 ETN9	d = 15	D = 42	B = 13	Self-aligning ball bearing
FAG	2302-2RS-TVH	d = 15	D = 42	B = 17	Self-aligning ball bearing
FAG	2302-TVH	d = 15	D = 42	B = 17	Self-aligning ball bearing
FAG	2302-TVH-C3	d = 15	D = 42	B = 17	Self-aligning ball bearing
KOYO	2302	d = 15	D = 42	B = 17	Self-aligning ball bearing
KOYO	23022RS	d = 15	D = 42	B = 17	Self-aligning ball bearing
NSK	2302	d = 15	D = 42	B = 17	Self-aligning ball bearing
SKF	2302	d = 15	D = 42	B = 17	Self-aligning ball bearing
SKF	2302 E-2RS1TN9	d = 15	D = 42	B = 17	Self-aligning ball bearing with seals on both sides

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
FAG	1203-TVH	d = 17	D = 40	B = 12	Self-aligning ball bearing
FAG	1203-TVH-C3	d = 17	D = 40	B = 12	Self-aligning ball bearing
FAG	1203-TVH-C3>N	d = 17	D = 40	B = 12	Self-aligning ball bearing
FAG	1203-TVH>N	d = 17	D = 40	B = 12	Self-aligning ball bearing
KOYO	1203	d = 17	D = 40	B = 12	Self-aligning ball bearing
NSK	1203	d = 17	D = 40	B = 12	Self-aligning ball bearing
SKF	1203 ETN9	d = 17	D = 40	B = 12	Self-aligning ball bearing
FAG	2203-2RS-TVH	d = 17	D = 40	B = 16	Self-aligning ball bearing
FAG	2203-2RS-TVH>N	d = 17	D = 40	B = 16	Self-aligning ball bearing
FAG	2203-TVH	d = 17	D = 40	B = 16	Self-aligning ball bearing
FAG	2203-TVH-C3	d = 17	D = 40	B = 16	Self-aligning ball bearing
FAG	2203-TVH-C3>N	d = 17	D = 40	B = 16	Self-aligning ball bearing
FAG	2203-TVH>N	d = 17	D = 40	B = 16	Self-aligning ball bearing
KOYO	2203	d = 17	D = 40	B = 16	Self-aligning ball bearing
KOYO	22032RS	d = 17	D = 40	B = 16	Self-aligning ball bearing
NSK	2203	d = 17	D = 40	B = 16	Self-aligning ball bearing
SKF	2203 E-2RS1TN9	d = 17	D = 40	B = 16	Self-aligning ball bearing with seals on both sides

Self-aligning ball bearings

Self-aligns ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
SKF	2203 ETN9	d = 17	D = 40	B = 16	Self-aligning ball bearing
FAG	1303-TVH	d = 17	D = 47	B = 14	Self-aligning ball bearing
KOYO	1303	d = 17	D = 47	B = 14	Self-aligning ball bearing
NSK	1303	d = 17	D = 47	B = 14	Self-aligning ball bearing
SKF	1303 EM	d = 17	D = 47	B = 14	Self-aligning ball bearing
SKF	1303 ETN9	d = 17	D = 47	B = 14	Self-aligning ball bearing
FAG	2303-2RS-TVH	d = 17	D = 47	B = 19	Self-aligning ball bearing
FAG	2303-TVH	d = 17	D = 47	B = 19	Self-aligning ball bearing
KOYO	2303	d = 17	D = 47	B = 19	Self-aligning ball bearing
KOYO	23032RS	d = 17	D = 47	B = 19	Self-aligning ball bearing
NSK	2303	d = 17	D = 47	B = 19	Self-aligning ball bearing
SKF	2303	d = 17	D = 47	B = 19	Self-aligning ball bearing
SKF	2303 E-2RS1TN9	d = 17	D = 47	B = 19	Self-aligning ball bearing with seals on both sides
FAG	1204-K-TVH-C3	d = 20	D = 47	B = 14	Self-aligning ball bearing
FAG	1204-TVH	d = 20	D = 47	B = 14	Self-aligning ball bearing
FAG	1204-TVH-C3	d = 20	D = 47	B = 14	Self-aligning ball bearing
FAG	1204-TVH-C3>N	d = 20	D = 47	B = 14	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
FAG	1204-TVH>N	d = 20	D = 47	B = 14	Self-aligning ball bearing
KOYO	1204	d = 20	D = 47	B = 14	Self-aligning ball bearing
NSK	1204	d = 20	D = 47	B = 14	Self-aligning ball bearing
NSK	1204K	d = 20	D = 47	B = 14	Self-aligning ball bearing
SKF	1204 ETN9	d = 20	D = 47	B = 14	Self-aligning ball bearing
FAG	2204-2RS-TVH	d = 20	D = 47	B = 18	Self-aligning ball bearing
FAG	2204-2RS-TVH>N	d = 20	D = 47	B = 18	Self-aligning ball bearing
FAG	2204-TVH	d = 20	D = 47	B = 18	Self-aligning ball bearing
FAG	2204-TVH-C3	d = 20	D = 47	B = 18	Self-aligning ball bearing
FAG	2204-TVH-C3>N	d = 20	D = 47	B = 18	Self-aligning ball bearing
FAG	2204-TVH>N	d = 20	D = 47	B = 18	Self-aligning ball bearing
KOYO	2204	d = 20	D = 47	B = 18	Self-aligning ball bearing
KOYO	22042RS	d = 20	D = 47	B = 18	Self-aligning ball bearing
NSK	2204	d = 20	D = 47	B = 18	Self-aligning ball bearing
NSK	2204K	d = 20	D = 47	B = 18	Self-aligning ball bearing
SKF	2204 E-2RS1TN9	d = 20	D = 47	B = 18	Self-aligning ball bearing with seals on both sides
SKF	2204 ETN9	d = 20	D = 47	B = 18	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
FAG	11204-TVH	d = 20	D = 47	B = 40	Self-aligning ball bearing
FAG	1304-K-TVH-C3	d = 20	D = 52	B = 15	Self-aligning ball bearing
FAG	1304-TVH	d = 20	D = 52	B = 15	Self-aligning ball bearing
FAG	1304-TVH-C3	d = 20	D = 52	B = 15	Self-aligning ball bearing
KOYO	1304	d = 20	D = 52	B = 15	Self-aligning ball bearing
NSK	1304	d = 20	D = 52	B = 15	Self-aligning ball bearing
NSK	1304K	d = 20	D = 52	B = 15	Self-aligning ball bearing
SKF	1304 ETN9	d = 20	D = 52	B = 15	Self-aligning ball bearing
FAG	2304-2RS-TVH	d = 20	D = 52	B = 21	Self-aligning ball bearing
FAG	2304-2RS-TVH-C3	d = 20	D = 52	B = 21	Self-aligning ball bearing
KOYO	2304	d = 20	D = 52	B = 21	Self-aligning ball bearing
KOYO	23042RS	d = 20	D = 52	B = 21	Self-aligning ball bearing
NSK	2304	d = 20	D = 52	B = 21	Self-aligning ball bearing
NSK	2304K	d = 20	D = 52	B = 21	Self-aligning ball bearing
SKF	2304 E-2RS1TN9	d = 20	D = 52	B = 21	Self-aligning ball bearing with seals on both sides
SKF	2304 M	d = 20	D = 52	B = 21	Self-aligning ball bearing
SKF	2304 TN9	d = 20	D = 52	B = 21	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
FAG	1205-K-TVH-C3	d = 25	D = 52	B = 15	Self-aligning ball bearing
FAG	1205-TVH	d = 25	D = 52	B = 15	Self-aligning ball bearing
FAG	1205-TVH-C3	d = 25	D = 52	B = 15	Self-aligning ball bearing
FAG	1205-TVH-C3>N	d = 25	D = 52	B = 15	Self-aligning ball bearing
FAG	1205-TVH>N	d = 25	D = 52	B = 15	Self-aligning ball bearing
KOYO	1205	d = 25	D = 52	B = 15	Self-aligning ball bearing
NSK	1205	d = 25	D = 52	B = 15	Self-aligning ball bearing
NSK	1205K	d = 25	D = 52	B = 15	Self-aligning ball bearing
SKF	1205 EM	d = 25	D = 52	B = 15	Self-aligning ball bearing
SKF	1205 ETN9	d = 25	D = 52	B = 15	Self-aligning ball bearing
FAG	2205-2RS-TVH	d = 25	D = 52	B = 18	Self-aligning ball bearing
FAG	2205-2RS-TVH-C3	d = 25	D = 52	B = 18	Self-aligning ball bearing
FAG	2205-2RS-TVH-C3>N	d = 25	D = 52	B = 18	Self-aligning ball bearing
FAG	2205-2RS-TVH>N	d = 25	D = 52	B = 18	Self-aligning ball bearing
FAG	2205-K-2RS-TVH	d = 25	D = 52	B = 18	Self-aligning ball bearing
FAG	2205-K-2RS-TVH-C3	d = 25	D = 52	B = 18	Self-aligning ball bearing
FAG	2205-K-TVH-C3	d = 25	D = 52	B = 18	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
FAG	2205-TVH	d = 25	D = 52	B = 18	Self-aligning ball bearing
FAG	2205-TVH-C3	d = 25	D = 52	B = 18	Self-aligning ball bearing
FAG	2205-TVH-C3>N	d = 25	D = 52	B = 18	Self-aligning ball bearing
FAG	2205-TVH>N	d = 25	D = 52	B = 18	Self-aligning ball bearing
KOYO	2205	d = 25	D = 52	B = 18	Self-aligning ball bearing
KOYO	22052RS	d = 25	D = 52	B = 18	Self-aligning ball bearing
NSK	2205	d = 25	D = 52	B = 18	Self-aligning ball bearing
NSK	2205K	d = 25	D = 52	B = 18	Self-aligning ball bearing
SKF	2205 E-2RS1TN9	d = 25	D = 52	B = 18	Self-aligning ball bearing with seals on both sides
SKF	2205 ETN9	d = 25	D = 52	B = 18	Self-aligning ball bearing
FAG	11205-TVH	d = 25	D = 52	B = 44	Self-aligning ball bearing
FAG	1305-K-TVH-C3	d = 25	D = 62	B = 17	Self-aligning ball bearing
FAG	1305-TVH	d = 25	D = 62	B = 17	Self-aligning ball bearing
FAG	1305-TVH-C3	d = 25	D = 62	B = 17	Self-aligning ball bearing
FAG	1305-TVH-C3>N	d = 25	D = 62	B = 17	Self-aligning ball bearing
FAG	1305-TVH>N	d = 25	D = 62	B = 17	Self-aligning ball bearing
KOYO	1305	d = 25	D = 62	B = 17	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
NSK	1305	d = 25	D = 62	B = 17	Self-aligning ball bearing
NSK	1305K	d = 25	D = 62	B = 17	Self-aligning ball bearing
SKF	1305 ETN9	d = 25	D = 62	B = 17	Self-aligning ball bearing
FAG	2305-2RS-TVH	d = 25	D = 62	B = 24	Self-aligning ball bearing
FAG	2305-2RS-TVH>N	d = 25	D = 62	B = 24	Self-aligning ball bearing
FAG	2305-K-TVH-C3	d = 25	D = 62	B = 24	Self-aligning ball bearing
FAG	2305-M	d = 25	D = 62	B = 24	Self-aligning ball bearing
FAG	2305-TVH	d = 25	D = 62	B = 24	Self-aligning ball bearing
FAG	2305-TVH-C3	d = 25	D = 62	B = 24	Self-aligning ball bearing
FAG	2305-TVH-C3>N	d = 25	D = 62	B = 24	Self-aligning ball bearing
FAG	2305-TVH>N	d = 25	D = 62	B = 24	Self-aligning ball bearing
KOYO	2305	d = 25	D = 62	B = 24	Self-aligning ball bearing
KOYO	23052RS	d = 25	D = 62	B = 24	Self-aligning ball bearing
NSK	2305	d = 25	D = 62	B = 24	Self-aligning ball bearing
NSK	2305K	d = 25	D = 62	B = 24	Self-aligning ball bearing
SKF	2305 E-2RS1TN9	d = 25	D = 62	B = 24	Self-aligning ball bearing with seals on both sides
SKF	2305 ETN9	d = 25	D = 62	B = 24	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
SKF	2305 M	d = 25	D = 62	B = 24	Self-aligning ball bearing
FAG	1206-K-TVH-C3	d = 30	D = 62	B = 16	Self-aligning ball bearing
FAG	1206-TVH	d = 30	D = 62	B = 16	Self-aligning ball bearing
FAG	1206-TVH-C3	d = 30	D = 62	B = 16	Self-aligning ball bearing
FAG	1206-TVH-C3>N	d = 30	D = 62	B = 16	Self-aligning ball bearing
FAG	1206-TVH>N	d = 30	D = 62	B = 16	Self-aligning ball bearing
KOYO	1206	d = 30	D = 62	B = 16	Self-aligning ball bearing
NSK	1206	d = 30	D = 62	B = 16	Self-aligning ball bearing
NSK	1206K	d = 30	D = 62	B = 16	Self-aligning ball bearing
SKF	1206 EM	d = 30	D = 62	B = 16	Self-aligning ball bearing
SKF	1206 ETN9	d = 30	D = 62	B = 16	Self-aligning ball bearing
FAG	2206-2RS-TVH	d = 30	D = 62	B = 20	Self-aligning ball bearing
FAG	2206-2RS-TVH>N	d = 30	D = 62	B = 20	Self-aligning ball bearing
FAG	2206-K-2RS-TVH-C3	d = 30	D = 62	B = 20	Self-aligning ball bearing
FAG	2206-K-TVH	d = 30	D = 62	B = 20	Self-aligning ball bearing
FAG	2206-K-TVH-C3	d = 30	D = 62	B = 20	Self-aligning ball bearing
FAG	2206-TVH	d = 30	D = 62	B = 20	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
FAG	2206-TVH-C3	d = 30	D = 62	B = 20	Self-aligning ball bearing
FAG	2206-TVH-C3>N	d = 30	D = 62	B = 20	Self-aligning ball bearing
FAG	2206-TVH>N	d = 30	D = 62	B = 20	Self-aligning ball bearing
KOYO	2206	d = 30	D = 62	B = 20	Self-aligning ball bearing
KOYO	22062RS	d = 30	D = 62	B = 20	Self-aligning ball bearing
NSK	2206	d = 30	D = 62	B = 20	Self-aligning ball bearing
NSK	2206K	d = 30	D = 62	B = 20	Self-aligning ball bearing
SKF	2206 E-2RS1TN9	d = 30	D = 62	B = 20	Self-aligning ball bearing with seals on both sides
SKF	2206 ETN9	d = 30	D = 62	B = 20	Self-aligning ball bearing
FAG	11206-TVH	d = 30	D = 62	B = 48	Self-aligning ball bearing
FAG	1306-K-TVH-C3	d = 30	D = 72	B = 19	Self-aligning ball bearing
FAG	1306-TVH	d = 30	D = 72	B = 19	Self-aligning ball bearing
FAG	1306-TVH-C3	d = 30	D = 72	B = 19	Self-aligning ball bearing
KOYO	1306	d = 30	D = 72	B = 19	Self-aligning ball bearing
NSK	1306	d = 30	D = 72	B = 19	Self-aligning ball bearing
NSK	1306K	d = 30	D = 72	B = 19	Self-aligning ball bearing
SKF	1306 ETN9	d = 30	D = 72	B = 19	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
FAG	2306-2RS-TVH	d = 30	D = 72	B = 27	Self-aligning ball bearing
FAG	2306-K-TVH-C3	d = 30	D = 72	B = 27	Self-aligning ball bearing
FAG	2306-M	d = 30	D = 72	B = 27	Self-aligning ball bearing
FAG	2306-TVH	d = 30	D = 72	B = 27	Self-aligning ball bearing
FAG	2306-TVH-C3	d = 30	D = 72	B = 27	Self-aligning ball bearing
KOYO	2306	d = 30	D = 72	B = 27	Self-aligning ball bearing
KOYO	23062RS	d = 30	D = 72	B = 27	Self-aligning ball bearing
NSK	2306	d = 30	D = 72	B = 27	Self-aligning ball bearing
NSK	2306K	d = 30	D = 72	B = 27	Self-aligning ball bearing
SKF	2306	d = 30	D = 72	B = 27	Self-aligning ball bearing
SKF	2306 E-2RS1TN9	d = 30	D = 72	B = 27	Self-aligning ball bearing with seals on both sides
SKF	2306 M	d = 30	D = 72	B = 27	Self-aligning ball bearing
FAG	1207-K-TVH-C3	d = 35	D = 72	B = 17	Self-aligning ball bearing
FAG	1207-TVH	d = 35	D = 72	B = 17	Self-aligning ball bearing
FAG	1207-TVH-C3	d = 35	D = 72	B = 17	Self-aligning ball bearing
KOYO	1207	d = 35	D = 72	B = 17	Self-aligning ball bearing
NSK	1207	d = 35	D = 72	B = 17	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
NSK	1207K	d = 35	D = 72	B = 17	Self-aligning ball bearing
SKF	1207 EM	d = 35	D = 72	B = 17	Self-aligning ball bearing
SKF	1207 ETN9	d = 35	D = 72	B = 17	Self-aligning ball bearing
FAG	2207-2RS-TVH	d = 35	D = 72	B = 23	Self-aligning ball bearing
FAG	2207-2RS-TVH-C3	d = 35	D = 72	B = 23	Self-aligning ball bearing
FAG	2207-K-2RS-TVH	d = 35	D = 72	B = 23	Self-aligning ball bearing
FAG	2207-K-2RS-TVH-C3	d = 35	D = 72	B = 23	Self-aligning ball bearing
FAG	2207-K-TVH-C3	d = 35	D = 72	B = 23	Self-aligning ball bearing
FAG	2207-TVH	d = 35	D = 72	B = 23	Self-aligning ball bearing
FAG	2207-TVH-C3	d = 35	D = 72	B = 23	Self-aligning ball bearing
KOYO	2207	d = 35	D = 72	B = 23	Self-aligning ball bearing
KOYO	22072RS	d = 35	D = 72	B = 23	Self-aligning ball bearing
NSK	2207	d = 35	D = 72	B = 23	Self-aligning ball bearing
NSK	2207K	d = 35	D = 72	B = 23	Self-aligning ball bearing
SKF	2207 E-2RS1TN9	d = 35	D = 72	B = 23	Self-aligning ball bearing with seals on both sides
SKF	2207 ETN9	d = 35	D = 72	B = 23	Self-aligning ball bearing
FAG	11207-TVH	d = 35	D = 72	B = 52	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
FAG	1307-K-TVH-C3	d = 35	D = 80	B = 21	Self-aligning ball bearing
FAG	1307-TVH	d = 35	D = 80	B = 21	Self-aligning ball bearing
FAG	1307-TVH-C3	d = 35	D = 80	B = 21	Self-aligning ball bearing
KOYO	1307	d = 35	D = 80	B = 21	Self-aligning ball bearing
NSK	1307	d = 35	D = 80	B = 21	Self-aligning ball bearing
NSK	1307K	d = 35	D = 80	B = 21	Self-aligning ball bearing
SKF	1307 ETN9	d = 35	D = 80	B = 21	Self-aligning ball bearing
FAG	2307-2RS-TVH	d = 35	D = 80	B = 31	Self-aligning ball bearing
FAG	2307-2RS-TVH-C3	d = 35	D = 80	B = 31	Self-aligning ball bearing
FAG	2307-K-TVH-C3	d = 35	D = 80	B = 31	Self-aligning ball bearing
FAG	2307-M	d = 35	D = 80	B = 31	Self-aligning ball bearing
FAG	2307-TVH	d = 35	D = 80	B = 31	Self-aligning ball bearing
FAG	2307-TVH-C3	d = 35	D = 80	B = 31	Self-aligning ball bearing
KOYO	2307	d = 35	D = 80	B = 31	Self-aligning ball bearing
KOYO	23072RS	d = 35	D = 80	B = 31	Self-aligning ball bearing
NSK	2307	d = 35	D = 80	B = 31	Self-aligning ball bearing
NSK	2307K	d = 35	D = 80	B = 31	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
SKF	2307 E-2RS1TN9	d = 35	D = 80	B = 31	Self-aligning ball bearing with seals on both sides
SKF	2307 EM	d = 35	D = 80	B = 31	Self-aligning ball bearing
SKF	2307 ETN9	d = 35	D = 80	B = 31	Self-aligning ball bearing
FAG	1208-K-TVH-C3	d = 40	D = 80	B = 18	Self-aligning ball bearing
FAG	1208-TVH	d = 40	D = 80	B = 18	Self-aligning ball bearing
FAG	1208-TVH-C3	d = 40	D = 80	B = 18	Self-aligning ball bearing
KOYO	1208	d = 40	D = 80	B = 18	Self-aligning ball bearing
NSK	1208	d = 40	D = 80	B = 18	Self-aligning ball bearing
NSK	1208K	d = 40	D = 80	B = 18	Self-aligning ball bearing
SKF	1208 ETN9	d = 40	D = 80	B = 18	Self-aligning ball bearing
FAG	2208-2RS-TVH	d = 40	D = 80	B = 23	Self-aligning ball bearing
FAG	2208-K-2RS-TVH-C3	d = 40	D = 80	B = 23	Self-aligning ball bearing
FAG	2208-K-TVH	d = 40	D = 80	B = 23	Self-aligning ball bearing
FAG	2208-K-TVH-C3	d = 40	D = 80	B = 23	Self-aligning ball bearing
FAG	2208-TVH	d = 40	D = 80	B = 23	Self-aligning ball bearing
FAG	2208-TVH-C3	d = 40	D = 80	B = 23	Self-aligning ball bearing
KOYO	2208	d = 40	D = 80	B = 23	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
KOYO	22082RS	d = 40	D = 80	B = 23	Self-aligning ball bearing
NSK	2208	d = 40	D = 80	B = 23	Self-aligning ball bearing
NSK	2208K	d = 40	D = 80	B = 23	Self-aligning ball bearing
SKF	2208 E-2RS1TN9	d = 40	D = 80	B = 23	Self-aligning ball bearing with seals on both sides
SKF	2208 ETN9	d = 40	D = 80	B = 23	Self-aligning ball bearing
FAG	11208-TVH	d = 40	D = 80	B = 56	Self-aligning ball bearing
FAG	1308-K-TVH-C3	d = 40	D = 90	B = 23	Self-aligning ball bearing
FAG	1308-TVH	d = 40	D = 90	B = 23	Self-aligning ball bearing
FAG	1308-TVH-C3	d = 40	D = 90	B = 23	Self-aligning ball bearing
KOYO	1308	d = 40	D = 90	B = 23	Self-aligning ball bearing
NSK	1308	d = 40	D = 90	B = 23	Self-aligning ball bearing
NSK	1308K	d = 40	D = 90	B = 23	Self-aligning ball bearing
SKF	1308 EM	d = 40	D = 90	B = 23	Self-aligning ball bearing
SKF	1308 ETN9	d = 40	D = 90	B = 23	Self-aligning ball bearing
FAG	2308-2RS-TVH	d = 40	D = 90	B = 33	Self-aligning ball bearing
FAG	2308-K-TVH	d = 40	D = 90	B = 33	Self-aligning ball bearing
FAG	2308-K-TVH-C3	d = 40	D = 90	B = 33	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
FAG	2308-M	d = 40	D = 90	B = 33	Self-aligning ball bearing
FAG	2308-M-C3	d = 40	D = 90	B = 33	Self-aligning ball bearing
FAG	2308-TVH	d = 40	D = 90	B = 33	Self-aligning ball bearing
FAG	2308-TVH-C3	d = 40	D = 90	B = 33	Self-aligning ball bearing
KOYO	2308	d = 40	D = 90	B = 33	Self-aligning ball bearing
KOYO	23082RS	d = 40	D = 90	B = 33	Self-aligning ball bearing
NSK	2308	d = 40	D = 90	B = 33	Self-aligning ball bearing
NSK	2308K	d = 40	D = 90	B = 33	Self-aligning ball bearing
SKF	2308 E-2RS1TN9	d = 40	D = 90	B = 33	Self-aligning ball bearing with seals on both sides
SKF	2308 EM	d = 40	D = 90	B = 33	Self-aligning ball bearing
SKF	2308 ETN9	d = 40	D = 90	B = 33	Self-aligning ball bearing
FAG	1209-K-TVH	d = 45	D = 85	B = 19	Self-aligning ball bearing
FAG	1209-K-TVH-C3	d = 45	D = 85	B = 19	Self-aligning ball bearing
FAG	1209-TVH	d = 45	D = 85	B = 19	Self-aligning ball bearing
FAG	1209-TVH-C3	d = 45	D = 85	B = 19	Self-aligning ball bearing
KOYO	1209	d = 45	D = 85	B = 19	Self-aligning ball bearing
NSK	1209	d = 45	D = 85	B = 19	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
NSK	1209K	d = 45	D = 85	B = 19	Self-aligning ball bearing
SKF	1209 ETN9	d = 45	D = 85	B = 19	Self-aligning ball bearing
FAG	2209-2RS-TVH	d = 45	D = 85	B = 23	Self-aligning ball bearing
FAG	2209-K-2RS-TVH	d = 45	D = 85	B = 23	Self-aligning ball bearing
FAG	2209-K-2RS-TVH-C3	d = 45	D = 85	B = 23	Self-aligning ball bearing
FAG	2209-K-TVH	d = 45	D = 85	B = 23	Self-aligning ball bearing
FAG	2209-K-TVH-C3	d = 45	D = 85	B = 23	Self-aligning ball bearing
FAG	2209-TVH	d = 45	D = 85	B = 23	Self-aligning ball bearing
FAG	2209-TVH-C3	d = 45	D = 85	B = 23	Self-aligning ball bearing
KOYO	2209	d = 45	D = 85	B = 23	Self-aligning ball bearing
KOYO	22092RS	d = 45	D = 85	B = 23	Self-aligning ball bearing
NSK	2209	d = 45	D = 85	B = 23	Self-aligning ball bearing
NSK	2209K	d = 45	D = 85	B = 23	Self-aligning ball bearing
SKF	2209 E-2RS1TN9	d = 45	D = 85	B = 23	Self-aligning ball bearing with seals on both sides
SKF	2209 ETN9	d = 45	D = 85	B = 23	Self-aligning ball bearing
FAG	11209-TVH	d = 45	D = 85	B = 58	Self-aligning ball bearing
FAG	1309-K-TVH	d = 45	D = 100	B = 25	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
FAG	1309-K-TVH-C3	d = 45	D = 100	B = 25	Self-aligning ball bearing
FAG	1309-TVH	d = 45	D = 100	B = 25	Self-aligning ball bearing
FAG	1309-TVH-C3	d = 45	D = 100	B = 25	Self-aligning ball bearing
FAG	1309-TVH-C3>N	d = 45	D = 100	B = 25	Self-aligning ball bearing
FAG	1309-TVH>N	d = 45	D = 100	B = 25	Self-aligning ball bearing
KOYO	1309	d = 45	D = 100	B = 25	Self-aligning ball bearing
NSK	1309	d = 45	D = 100	B = 25	Self-aligning ball bearing
NSK	1309K	d = 45	D = 100	B = 25	Self-aligning ball bearing
SKF	1309 ETN9	d = 45	D = 100	B = 25	Self-aligning ball bearing
FAG	2309-2RS-TVH	d = 45	D = 100	B = 36	Self-aligning ball bearing
FAG	2309-K-2RS-TVH-C3	d = 45	D = 100	B = 36	Self-aligning ball bearing
FAG	2309-K-TVH-C3	d = 45	D = 100	B = 36	Self-aligning ball bearing
FAG	2309-M	d = 45	D = 100	B = 36	Self-aligning ball bearing
FAG	2309-M-C3	d = 45	D = 100	B = 36	Self-aligning ball bearing
FAG	2309-TVH	d = 45	D = 100	B = 36	Self-aligning ball bearing
FAG	2309-TVH-C3	d = 45	D = 100	B = 36	Self-aligning ball bearing
KOYO	2309	d = 45	D = 100	B = 36	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
KOYO	23092RS	d = 45	D = 100	B = 36	Self-aligning ball bearing
NSK	2309	d = 45	D = 100	B = 36	Self-aligning ball bearing
NSK	2309K	d = 45	D = 100	B = 36	Self-aligning ball bearing
SKF	2309 E-2RS1TN9	d = 45	D = 100	B = 36	Self-aligning ball bearing with seals on both sides
SKF	2309 EM	d = 45	D = 100	B = 36	Self-aligning ball bearing
SKF	2309 ETN9	d = 45	D = 100	B = 36	Self-aligning ball bearing
FAG	1210-K-TVH	d = 50	D = 90	B = 20	Self-aligning ball bearing
FAG	1210-K-TVH-C3	d = 50	D = 90	B = 20	Self-aligning ball bearing
FAG	1210-TVH	d = 50	D = 90	B = 20	Self-aligning ball bearing
FAG	1210-TVH-C3	d = 50	D = 90	B = 20	Self-aligning ball bearing
KOYO	1210	d = 50	D = 90	B = 20	Self-aligning ball bearing
NSK	1210	d = 50	D = 90	B = 20	Self-aligning ball bearing
NSK	1210K	d = 50	D = 90	B = 20	Self-aligning ball bearing
SKF	1210 ETN9	d = 50	D = 90	B = 20	Self-aligning ball bearing
FAG	2210-2RS-TVH	d = 50	D = 90	B = 23	Self-aligning ball bearing
FAG	2210-2RS-TVH-C3	d = 50	D = 90	B = 23	Self-aligning ball bearing
FAG	2210-K-2RS-TVH	d = 50	D = 90	B = 23	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
FAG	2210-K-2RS-TVH-C3	d = 50	D = 90	B = 23	Self-aligning ball bearing
FAG	2210-K-TVH	d = 50	D = 90	B = 23	Self-aligning ball bearing
FAG	2210-K-TVH-C3	d = 50	D = 90	B = 23	Self-aligning ball bearing
FAG	2210-TVH	d = 50	D = 90	B = 23	Self-aligning ball bearing
FAG	2210-TVH-C3	d = 50	D = 90	B = 23	Self-aligning ball bearing
KOYO	2210	d = 50	D = 90	B = 23	Self-aligning ball bearing
KOYO	22102RS	d = 50	D = 90	B = 23	Self-aligning ball bearing
NSK	2210	d = 50	D = 90	B = 23	Self-aligning ball bearing
NSK	2210K	d = 50	D = 90	B = 23	Self-aligning ball bearing
SKF	2210 E-2RS1TN9	d = 50	D = 90	B = 23	Self-aligning ball bearing with seals on both sides
SKF	2210 ETN9	d = 50	D = 90	B = 23	Self-aligning ball bearing
FAG	11210-TVH	d = 50	D = 90	B = 58	Self-aligning ball bearing
FAG	1310-K-TVH	d = 50	D = 110	B = 27	Self-aligning ball bearing
FAG	1310-K-TVH-C3	d = 50	D = 110	B = 27	Self-aligning ball bearing
FAG	1310-TVH	d = 50	D = 110	B = 27	Self-aligning ball bearing
FAG	1310-TVH-C3	d = 50	D = 110	B = 27	Self-aligning ball bearing
KOYO	1310	d = 50	D = 110	B = 27	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
NSK	1310	d = 50	D = 110	B = 27	Self-aligning ball bearing
NSK	1310K	d = 50	D = 110	B = 27	Self-aligning ball bearing
SKF	1310 ETN9	d = 50	D = 110	B = 27	Self-aligning ball bearing
FAG	2310-2RS-TVH	d = 50	D = 110	B = 40	Self-aligning ball bearing
FAG	2310-2RS-TVH-C3	d = 50	D = 110	B = 40	Self-aligning ball bearing
FAG	2310-K-2RS-TVH-C3	d = 50	D = 110	B = 40	Self-aligning ball bearing
FAG	2310-K-TVH	d = 50	D = 110	B = 40	Self-aligning ball bearing
FAG	2310-K-TVH-C3	d = 50	D = 110	B = 40	Self-aligning ball bearing
FAG	2310-M	d = 50	D = 110	B = 40	Self-aligning ball bearing
FAG	2310-M-C3	d = 50	D = 110	B = 40	Self-aligning ball bearing
FAG	2310-TVH	d = 50	D = 110	B = 40	Self-aligning ball bearing
FAG	2310-TVH-C3	d = 50	D = 110	B = 40	Self-aligning ball bearing
KOYO	2310	d = 50	D = 110	B = 40	Self-aligning ball bearing
KOYO	23102RS	d = 50	D = 110	B = 40	Self-aligning ball bearing
NSK	2310	d = 50	D = 110	B = 40	Self-aligning ball bearing
NSK	2310K	d = 50	D = 110	B = 40	Self-aligning ball bearing
SKF	2310	d = 50	D = 110	B = 40	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
SKF	2310 E-2RS1TN9	d = 50	D = 110	B = 40	Self-aligning ball bearing with seals on both sides
SKF	2310 M	d = 50	D = 110	B = 40	Self-aligning ball bearing
FAG	1211-K-TVH	d = 55	D = 100	B = 21	Self-aligning ball bearing
FAG	1211-K-TVH-C3	d = 55	D = 100	B = 21	Self-aligning ball bearing
FAG	1211-TVH	d = 55	D = 100	B = 21	Self-aligning ball bearing
FAG	1211-TVH-C3	d = 55	D = 100	B = 21	Self-aligning ball bearing
FAG	1211-TVH-C3>N	d = 55	D = 100	B = 21	Self-aligning ball bearing
FAG	1211-TVH>N	d = 55	D = 100	B = 21	Self-aligning ball bearing
KOYO	1211	d = 55	D = 100	B = 21	Self-aligning ball bearing
NSK	1211	d = 55	D = 100	B = 21	Self-aligning ball bearing
NSK	1211K	d = 55	D = 100	B = 21	Self-aligning ball bearing
SKF	1211 ETN9	d = 55	D = 100	B = 21	Self-aligning ball bearing
FAG	2211-2RS-TVH	d = 55	D = 100	B = 25	Self-aligning ball bearing
FAG	2211-2RS-TVH>N	d = 55	D = 100	B = 25	Self-aligning ball bearing
FAG	2211-K-2RS-TVH-C3	d = 55	D = 100	B = 25	Self-aligning ball bearing
FAG	2211-K-TVH	d = 55	D = 100	B = 25	Self-aligning ball bearing
FAG	2211-K-TVH-C3	d = 55	D = 100	B = 25	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
FAG	2211-TVH	d = 55	D = 100	B = 25	Self-aligning ball bearing
FAG	2211-TVH-C3	d = 55	D = 100	B = 25	Self-aligning ball bearing
FAG	2211-TVH-C3>N	d = 55	D = 100	B = 25	Self-aligning ball bearing
FAG	2211-TVH>N	d = 55	D = 100	B = 25	Self-aligning ball bearing
KOYO	2211	d = 55	D = 100	B = 25	Self-aligning ball bearing
KOYO	22112RS	d = 55	D = 100	B = 25	Self-aligning ball bearing
NSK	2211	d = 55	D = 100	B = 25	Self-aligning ball bearing
NSK	2211K	d = 55	D = 100	B = 25	Self-aligning ball bearing
SKF	2211 E-2RS1TN9	d = 55	D = 100	B = 25	Self-aligning ball bearing with seals on both sides
SKF	2211 ETN9	d = 55	D = 100	B = 25	Self-aligning ball bearing
FAG	1311-K-TVH	d = 55	D = 120	B = 29	Self-aligning ball bearing
FAG	1311-K-TVH-C3	d = 55	D = 120	B = 29	Self-aligning ball bearing
FAG	1311-TVH	d = 55	D = 120	B = 29	Self-aligning ball bearing
FAG	1311-TVH-C3	d = 55	D = 120	B = 29	Self-aligning ball bearing
KOYO	1311	d = 55	D = 120	B = 29	Self-aligning ball bearing
NSK	1311	d = 55	D = 120	B = 29	Self-aligning ball bearing
NSK	1311K	d = 55	D = 120	B = 29	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
SKF	1311 ETN9	d = 55	D = 120	B = 29	Self-aligning ball bearing
FAG	2311-2RS-TVH	d = 55	D = 120	B = 43	Self-aligning ball bearing
FAG	2311-2RS-TVH-C3	d = 55	D = 120	B = 43	Self-aligning ball bearing
FAG	2311-K-2RS-TVH-C3	d = 55	D = 120	B = 43	Self-aligning ball bearing
FAG	2311-K-TVH-C3	d = 55	D = 120	B = 43	Self-aligning ball bearing
FAG	2311-TVH	d = 55	D = 120	B = 43	Self-aligning ball bearing
FAG	2311-TVH-C3	d = 55	D = 120	B = 43	Self-aligning ball bearing
KOYO	2311	d = 55	D = 120	B = 43	Self-aligning ball bearing
NSK	2311	d = 55	D = 120	B = 43	Self-aligning ball bearing
NSK	2311K	d = 55	D = 120	B = 43	Self-aligning ball bearing
SKF	2311	d = 55	D = 120	B = 43	Self-aligning ball bearing
SKF	2311 M	d = 55	D = 120	B = 43	Self-aligning ball bearing
FAG	1212-K-TVH	d = 60	D = 110	B = 22	Self-aligning ball bearing
FAG	1212-K-TVH-C3	d = 60	D = 110	B = 22	Self-aligning ball bearing
FAG	1212-TVH	d = 60	D = 110	B = 22	Self-aligning ball bearing
FAG	1212-TVH-C3	d = 60	D = 110	B = 22	Self-aligning ball bearing
FAG	1212-TVH-C3>N	d = 60	D = 110	B = 22	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
FAG	1212-TVH>N	d = 60	D = 110	B = 22	Self-aligning ball bearing
KOYO	1212	d = 60	D = 110	B = 22	Self-aligning ball bearing
NSK	1212	d = 60	D = 110	B = 22	Self-aligning ball bearing
NSK	1212K	d = 60	D = 110	B = 22	Self-aligning ball bearing
SKF	1212 ETN9	d = 60	D = 110	B = 22	Self-aligning ball bearing
FAG	2212-2RS-TVH	d = 60	D = 110	B = 28	Self-aligning ball bearing
FAG	2212-2RS-TVH-C3	d = 60	D = 110	B = 28	Self-aligning ball bearing
FAG	2212-2RS-TVH-C3>N	d = 60	D = 110	B = 28	Self-aligning ball bearing
FAG	2212-2RS-TVH>N	d = 60	D = 110	B = 28	Self-aligning ball bearing
FAG	2212-K-2RS-TVH-C3	d = 60	D = 110	B = 28	Self-aligning ball bearing
FAG	2212-K-TVH	d = 60	D = 110	B = 28	Self-aligning ball bearing
FAG	2212-K-TVH-C3	d = 60	D = 110	B = 28	Self-aligning ball bearing
FAG	2212-TVH	d = 60	D = 110	B = 28	Self-aligning ball bearing
FAG	2212-TVH-C3	d = 60	D = 110	B = 28	Self-aligning ball bearing
FAG	2212-TVH-C3>N	d = 60	D = 110	B = 28	Self-aligning ball bearing
FAG	2212-TVH>N	d = 60	D = 110	B = 28	Self-aligning ball bearing
KOYO	2212	d = 60	D = 110	B = 28	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
NSK	2212	d = 60	D = 110	B = 28	Self-aligning ball bearing
NSK	2212K	d = 60	D = 110	B = 28	Self-aligning ball bearing
SKF	2212 E-2RS1TN9	d = 60	D = 110	B = 28	Self-aligning ball bearing with seals on both sides
SKF	2212 ETN9	d = 60	D = 110	B = 28	Self-aligning ball bearing
FAG	11212-TVH	d = 60	D = 110	B = 62	Self-aligning ball bearing
FAG	1312-K-TVH	d = 60	D = 130	B = 31	Self-aligning ball bearing
FAG	1312-K-TVH-C3	d = 60	D = 130	B = 31	Self-aligning ball bearing
FAG	1312-TVH	d = 60	D = 130	B = 31	Self-aligning ball bearing
FAG	1312-TVH-C3	d = 60	D = 130	B = 31	Self-aligning ball bearing
KOYO	1312	d = 60	D = 130	B = 31	Self-aligning ball bearing
NSK	1312	d = 60	D = 130	B = 31	Self-aligning ball bearing
NSK	1312K	d = 60	D = 130	B = 31	Self-aligning ball bearing
SKF	1312 ETN9	d = 60	D = 130	B = 31	Self-aligning ball bearing
FAG	2312-K-TVH-C3	d = 60	D = 130	B = 46	Self-aligning ball bearing
FAG	2312-M	d = 60	D = 130	B = 46	Self-aligning ball bearing
FAG	2312-M-C3	d = 60	D = 130	B = 46	Self-aligning ball bearing
FAG	2312-TVH	d = 60	D = 130	B = 46	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
FAG	2312-TVH-C3	d = 60	D = 130	B = 46	Self-aligning ball bearing
KOYO	2312	d = 60	D = 130	B = 46	Self-aligning ball bearing
NSK	2312	d = 60	D = 130	B = 46	Self-aligning ball bearing
NSK	2312K	d = 60	D = 130	B = 46	Self-aligning ball bearing
SKF	2312	d = 60	D = 130	B = 46	Self-aligning ball bearing
SKF	2312 M	d = 60	D = 130	B = 46	Self-aligning ball bearing
FAG	1213-K-TVH	d = 65	D = 120	B = 23	Self-aligning ball bearing
FAG	1213-K-TVH-C3	d = 65	D = 120	B = 23	Self-aligning ball bearing
FAG	1213-TVH	d = 65	D = 120	B = 23	Self-aligning ball bearing
FAG	1213-TVH-C3	d = 65	D = 120	B = 23	Self-aligning ball bearing
FAG	1213-TVH-C3>N	d = 65	D = 120	B = 23	Self-aligning ball bearing
FAG	1213-TVH>N	d = 65	D = 120	B = 23	Self-aligning ball bearing
KOYO	1213	d = 65	D = 120	B = 23	Self-aligning ball bearing
NSK	1213	d = 65	D = 120	B = 23	Self-aligning ball bearing
NSK	1213K	d = 65	D = 120	B = 23	Self-aligning ball bearing
SKF	1213 ETN9	d = 65	D = 120	B = 23	Self-aligning ball bearing
FAG	2213-2RS-TVH	d = 65	D = 120	B = 31	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
FAG	2213-2RS-TVH>N	d = 65	D = 120	B = 31	Self-aligning ball bearing
FAG	2213-K-2RS-TVH	d = 65	D = 120	B = 31	Self-aligning ball bearing
FAG	2213-K-2RS-TVH-C3	d = 65	D = 120	B = 31	Self-aligning ball bearing
FAG	2213-K-TVH-C3	d = 65	D = 120	B = 31	Self-aligning ball bearing
FAG	2213-TVH	d = 65	D = 120	B = 31	Self-aligning ball bearing
FAG	2213-TVH-C3	d = 65	D = 120	B = 31	Self-aligning ball bearing
FAG	2213-TVH-C3>N	d = 65	D = 120	B = 31	Self-aligning ball bearing
FAG	2213-TVH>N	d = 65	D = 120	B = 31	Self-aligning ball bearing
KOYO	2213	d = 65	D = 120	B = 31	Self-aligning ball bearing
NSK	2213	d = 65	D = 120	B = 31	Self-aligning ball bearing
NSK	2213K	d = 65	D = 120	B = 31	Self-aligning ball bearing
SKF	2213 E-2RS1TN9	d = 65	D = 120	B = 31	Self-aligning ball bearing with seals on both sides
SKF	2213 ETN9	d = 65	D = 120	B = 31	Self-aligning ball bearing
FAG	1313-K-TVH-C3	d = 65	D = 140	B = 33	Self-aligning ball bearing
FAG	1313-TVH	d = 65	D = 140	B = 33	Self-aligning ball bearing
FAG	1313-TVH-C3	d = 65	D = 140	B = 33	Self-aligning ball bearing
KOYO	1313	d = 65	D = 140	B = 33	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
NSK	1313	d = 65	D = 140	B = 33	Self-aligning ball bearing
NSK	1313K	d = 65	D = 140	B = 33	Self-aligning ball bearing
SKF	1313 ETN9	d = 65	D = 140	B = 33	Self-aligning ball bearing
FAG	2313-K-M-C3	d = 65	D = 140	B = 48	Self-aligning ball bearing
FAG	2313-K-TVH-C3	d = 65	D = 140	B = 48	Self-aligning ball bearing
FAG	2313-M	d = 65	D = 140	B = 48	Self-aligning ball bearing
FAG	2313-TVH	d = 65	D = 140	B = 48	Self-aligning ball bearing
FAG	2313-TVH-C3	d = 65	D = 140	B = 48	Self-aligning ball bearing
NSK	2313	d = 65	D = 140	B = 48	Self-aligning ball bearing
NSK	2313K	d = 65	D = 140	B = 48	Self-aligning ball bearing
SKF	2313	d = 65	D = 140	B = 48	Self-aligning ball bearing
SKF	2313 M	d = 65	D = 140	B = 48	Self-aligning ball bearing
FAG	1214-K-TVH-C3	d = 70	D = 125	B = 24	Self-aligning ball bearing
FAG	1214-TVH	d = 70	D = 125	B = 24	Self-aligning ball bearing
FAG	1214-TVH-C3	d = 70	D = 125	B = 24	Self-aligning ball bearing
FAG	1214-TVH-C3>N	d = 70	D = 125	B = 24	Self-aligning ball bearing
FAG	1214-TVH>N	d = 70	D = 125	B = 24	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
KOYO	1214	d = 70	D = 125	B = 24	Self-aligning ball bearing
NSK	1214	d = 70	D = 125	B = 24	Self-aligning ball bearing
SKF	1214 ETN9	d = 70	D = 125	B = 24	Self-aligning ball bearing
FAG	2214-2RS-TVH	d = 70	D = 125	B = 31	Self-aligning ball bearing
FAG	2214-M	d = 70	D = 125	B = 31	Self-aligning ball bearing
FAG	2214-M-C3	d = 70	D = 125	B = 31	Self-aligning ball bearing
NSK	2214	d = 70	D = 125	B = 31	Self-aligning ball bearing
SKF	2214	d = 70	D = 125	B = 31	Self-aligning ball bearing
SKF	2214 E-2RS1TN9	d = 70	D = 125	B = 31	Self-aligning ball bearing with seals on both sides
FAG	1314-M	d = 70	D = 150	B = 35	Self-aligning ball bearing
KOYO	1314	d = 70	D = 150	B = 35	Self-aligning ball bearing
NSK	1314	d = 70	D = 150	B = 35	Self-aligning ball bearing
SKF	1314	d = 70	D = 150	B = 35	Self-aligning ball bearing
FAG	2314-M	d = 70	D = 150	B = 51	Self-aligning ball bearing
FAG	2314-M-C3	d = 70	D = 150	B = 51	Self-aligning ball bearing
NSK	2314	d = 70	D = 150	B = 51	Self-aligning ball bearing
SKF	2314	d = 70	D = 150	B = 51	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
SKF	2314 M	d = 70	D = 150	B = 51	Self-aligning ball bearing
FAG	1215-K-TVH	d = 75	D = 130	B = 25	Self-aligning ball bearing
FAG	1215-K-TVH-C3	d = 75	D = 130	B = 25	Self-aligning ball bearing
FAG	1215-TVH	d = 75	D = 130	B = 25	Self-aligning ball bearing
FAG	1215-TVH-C3	d = 75	D = 130	B = 25	Self-aligning ball bearing
FAG	1215-TVH-C3>N	d = 75	D = 130	B = 25	Self-aligning ball bearing
FAG	1215-TVH>N	d = 75	D = 130	B = 25	Self-aligning ball bearing
KOYO	1215	d = 75	D = 130	B = 25	Self-aligning ball bearing
NSK	1215	d = 75	D = 130	B = 25	Self-aligning ball bearing
NSK	1215K	d = 75	D = 130	B = 25	Self-aligning ball bearing
SKF	1215	d = 75	D = 130	B = 25	Self-aligning ball bearing
FAG	2215-K-TVH	d = 75	D = 130	B = 31	Self-aligning ball bearing
FAG	2215-K-TVH-C3	d = 75	D = 130	B = 31	Self-aligning ball bearing
FAG	2215-TVH	d = 75	D = 130	B = 31	Self-aligning ball bearing
FAG	2215-TVH-C3	d = 75	D = 130	B = 31	Self-aligning ball bearing
FAG	2215-TVH-C3>N	d = 75	D = 130	B = 31	Self-aligning ball bearing
FAG	2215-TVH>N	d = 75	D = 130	B = 31	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
NSK	2215	d = 75	D = 130	B = 31	Self-aligning ball bearing
NSK	2215K	d = 75	D = 130	B = 31	Self-aligning ball bearing
SKF	2215 ETN9	d = 75	D = 130	B = 31	Self-aligning ball bearing
FAG	1315-K-M-C3	d = 75	D = 160	B = 37	Self-aligning ball bearing
FAG	1315-M	d = 75	D = 160	B = 37	Self-aligning ball bearing
FAG	1315-M-C3	d = 75	D = 160	B = 37	Self-aligning ball bearing
KOYO	1315	d = 75	D = 160	B = 37	Self-aligning ball bearing
NSK	1315	d = 75	D = 160	B = 37	Self-aligning ball bearing
NSK	1315K	d = 75	D = 160	B = 37	Self-aligning ball bearing
SKF	1315	d = 75	D = 160	B = 37	Self-aligning ball bearing
FAG	2315-K-M-C3	d = 75	D = 160	B = 55	Self-aligning ball bearing
FAG	2315-M	d = 75	D = 160	B = 55	Self-aligning ball bearing
FAG	2315-M-C3	d = 75	D = 160	B = 55	Self-aligning ball bearing
NSK	2315	d = 75	D = 160	B = 55	Self-aligning ball bearing
NSK	2315K	d = 75	D = 160	B = 55	Self-aligning ball bearing
SKF	2315	d = 75	D = 160	B = 55	Self-aligning ball bearing
SKF	2315 M	d = 75	D = 160	B = 55	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
FAG	1216-K-TVH-C3	d = 80	D = 140	B = 26	Self-aligning ball bearing
FAG	1216-TVH	d = 80	D = 140	B = 26	Self-aligning ball bearing
FAG	1216-TVH-C3	d = 80	D = 140	B = 26	Self-aligning ball bearing
FAG	1216-TVH-C3>N	d = 80	D = 140	B = 26	Self-aligning ball bearing
FAG	1216-TVH>N	d = 80	D = 140	B = 26	Self-aligning ball bearing
KOYO	1216	d = 80	D = 140	B = 26	Self-aligning ball bearing
NSK	1216	d = 80	D = 140	B = 26	Self-aligning ball bearing
NSK	1216K	d = 80	D = 140	B = 26	Self-aligning ball bearing
SKF	1216	d = 80	D = 140	B = 26	Self-aligning ball bearing
FAG	2216-2RS-TVH	d = 80	D = 140	B = 33	Self-aligning ball bearing
FAG	2216-K-TVH	d = 80	D = 140	B = 33	Self-aligning ball bearing
FAG	2216-K-TVH-C3	d = 80	D = 140	B = 33	Self-aligning ball bearing
FAG	2216-TVH	d = 80	D = 140	B = 33	Self-aligning ball bearing
FAG	2216-TVH-C3	d = 80	D = 140	B = 33	Self-aligning ball bearing
FAG	2216-TVH-C3>N	d = 80	D = 140	B = 33	Self-aligning ball bearing
FAG	2216-TVH>N	d = 80	D = 140	B = 33	Self-aligning ball bearing
NSK	2216	d = 80	D = 140	B = 33	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
NSK	2216K	d = 80	D = 140	B = 33	Self-aligning ball bearing
SKF	2216 ETN9	d = 80	D = 140	B = 33	Self-aligning ball bearing
FAG	1316-K-M-C3	d = 80	D = 170	B = 39	Self-aligning ball bearing
FAG	1316-M	d = 80	D = 170	B = 39	Self-aligning ball bearing
FAG	1316-M-C3	d = 80	D = 170	B = 39	Self-aligning ball bearing
KOYO	1316	d = 80	D = 170	B = 39	Self-aligning ball bearing
NSK	1316	d = 80	D = 170	B = 39	Self-aligning ball bearing
NSK	1316K	d = 80	D = 170	B = 39	Self-aligning ball bearing
SKF	1316	d = 80	D = 170	B = 39	Self-aligning ball bearing
FAG	2316-K-M-C3	d = 80	D = 170	B = 58	Self-aligning ball bearing
FAG	2316-M	d = 80	D = 170	B = 58	Self-aligning ball bearing
FAG	2316-M-C3	d = 80	D = 170	B = 58	Self-aligning ball bearing
NSK	2316	d = 80	D = 170	B = 58	Self-aligning ball bearing
NSK	2316K	d = 80	D = 170	B = 58	Self-aligning ball bearing
SKF	2316	d = 80	D = 170	B = 58	Self-aligning ball bearing
SKF	2316 M	d = 80	D = 170	B = 58	Self-aligning ball bearing
FAG	1217-K-TVH	d = 85	D = 150	B = 28	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
FAG	1217-K-TVH-C3	d = 85	D = 150	B = 28	Self-aligning ball bearing
FAG	1217-TVH	d = 85	D = 150	B = 28	Self-aligning ball bearing
FAG	1217-TVH-C3	d = 85	D = 150	B = 28	Self-aligning ball bearing
FAG	1217-TVH-C3>N	d = 85	D = 150	B = 28	Self-aligning ball bearing
FAG	1217-TVH>N	d = 85	D = 150	B = 28	Self-aligning ball bearing
KOYO	1217	d = 85	D = 150	B = 28	Self-aligning ball bearing
NSK	1217	d = 85	D = 150	B = 28	Self-aligning ball bearing
NSK	1217K	d = 85	D = 150	B = 28	Self-aligning ball bearing
SKF	1217	d = 85	D = 150	B = 28	Self-aligning ball bearing
FAG	2217-K-M	d = 85	D = 150	B = 36	Self-aligning ball bearing
FAG	2217-K-M-C3	d = 85	D = 150	B = 36	Self-aligning ball bearing
FAG	2217-M	d = 85	D = 150	B = 36	Self-aligning ball bearing
FAG	2217-M-C3	d = 85	D = 150	B = 36	Self-aligning ball bearing
NSK	2217	d = 85	D = 150	B = 36	Self-aligning ball bearing
NSK	2217K	d = 85	D = 150	B = 36	Self-aligning ball bearing
SKF	2217	d = 85	D = 150	B = 36	Self-aligning ball bearing
FAG	1317-K-M-C3	d = 85	D = 180	B = 41	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
FAG	1317-M	d = 85	D = 180	B = 41	Self-aligning ball bearing
FAG	1317-M-C3	d = 85	D = 180	B = 41	Self-aligning ball bearing
KOYO	1317	d = 85	D = 180	B = 41	Self-aligning ball bearing
NSK	1317	d = 85	D = 180	B = 41	Self-aligning ball bearing
NSK	1317K	d = 85	D = 180	B = 41	Self-aligning ball bearing
SKF	1317	d = 85	D = 180	B = 41	Self-aligning ball bearing
FAG	2317-K-M	d = 85	D = 180	B = 60	Self-aligning ball bearing
FAG	2317-K-M-C3	d = 85	D = 180	B = 60	Self-aligning ball bearing
FAG	2317-M	d = 85	D = 180	B = 60	Self-aligning ball bearing
FAG	2317-M-C3	d = 85	D = 180	B = 60	Self-aligning ball bearing
NSK	2317	d = 85	D = 180	B = 60	Self-aligning ball bearing
NSK	2317K	d = 85	D = 180	B = 60	Self-aligning ball bearing
SKF	2317 M	d = 85	D = 180	B = 60	Self-aligning ball bearing
FAG	1218-K-TVH	d = 90	D = 160	B = 30	Self-aligning ball bearing
FAG	1218-K-TVH-C3	d = 90	D = 160	B = 30	Self-aligning ball bearing
FAG	1218-TVH	d = 90	D = 160	B = 30	Self-aligning ball bearing
FAG	1218-TVH-C3	d = 90	D = 160	B = 30	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
KOYO	1218	d = 90	D = 160	B = 30	Self-aligning ball bearing
NSK	1218	d = 90	D = 160	B = 30	Self-aligning ball bearing
NSK	1218K	d = 90	D = 160	B = 30	Self-aligning ball bearing
SKF	1218	d = 90	D = 160	B = 30	Self-aligning ball bearing
FAG	2218-K-TVH	d = 90	D = 160	B = 40	Self-aligning ball bearing
FAG	2218-K-TVH-C3	d = 90	D = 160	B = 40	Self-aligning ball bearing
FAG	2218-TVH	d = 90	D = 160	B = 40	Self-aligning ball bearing
FAG	2218-TVH-C3	d = 90	D = 160	B = 40	Self-aligning ball bearing
NSK	2218	d = 90	D = 160	B = 40	Self-aligning ball bearing
NSK	2218K	d = 90	D = 160	B = 40	Self-aligning ball bearing
SKF	2218	d = 90	D = 160	B = 40	Self-aligning ball bearing
FAG	1318-K-M-C3	d = 90	D = 190	B = 43	Self-aligning ball bearing
FAG	1318-M	d = 90	D = 190	B = 43	Self-aligning ball bearing
FAG	1318-M-C3	d = 90	D = 190	B = 43	Self-aligning ball bearing
KOYO	1318	d = 90	D = 190	B = 43	Self-aligning ball bearing
NSK	1318	d = 90	D = 190	B = 43	Self-aligning ball bearing
NSK	1318K	d = 90	D = 190	B = 43	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
SKF	1318	d = 90	D = 190	B = 43	Self-aligning ball bearing
FAG	2318-K-M	d = 90	D = 190	B = 64	Self-aligning ball bearing
FAG	2318-K-M-C3	d = 90	D = 190	B = 64	Self-aligning ball bearing
FAG	2318-M	d = 90	D = 190	B = 64	Self-aligning ball bearing
FAG	2318-M-C3	d = 90	D = 190	B = 64	Self-aligning ball bearing
NSK	2318	d = 90	D = 190	B = 64	Self-aligning ball bearing
NSK	2318K	d = 90	D = 190	B = 64	Self-aligning ball bearing
SKF	2318 M	d = 90	D = 190	B = 64	Self-aligning ball bearing
FAG	1219-K-M	d = 95	D = 170	B = 32	Self-aligning ball bearing
FAG	1219-K-M-C3	d = 95	D = 170	B = 32	Self-aligning ball bearing
FAG	1219-M	d = 95	D = 170	B = 32	Self-aligning ball bearing
NSK	1219	d = 95	D = 170	B = 32	Self-aligning ball bearing
NSK	1219K	d = 95	D = 170	B = 32	Self-aligning ball bearing
SKF	1219	d = 95	D = 170	B = 32	Self-aligning ball bearing
FAG	2219-K-M	d = 95	D = 170	B = 43	Self-aligning ball bearing
FAG	2219-K-M-C3	d = 95	D = 170	B = 43	Self-aligning ball bearing
FAG	2219-M	d = 95	D = 170	B = 43	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
FAG	2219-M-C3	d = 95	D = 170	B = 43	Self-aligning ball bearing
NSK	2219	d = 95	D = 170	B = 43	Self-aligning ball bearing
NSK	2219K	d = 95	D = 170	B = 43	Self-aligning ball bearing
SKF	2219 M	d = 95	D = 170	B = 43	Self-aligning ball bearing
FAG	1319-K-M-C3	d = 95	D = 200	B = 45	Self-aligning ball bearing
FAG	1319-M	d = 95	D = 200	B = 45	Self-aligning ball bearing
NSK	1319	d = 95	D = 200	B = 45	Self-aligning ball bearing
NSK	1319K	d = 95	D = 200	B = 45	Self-aligning ball bearing
SKF	1319	d = 95	D = 200	B = 45	Self-aligning ball bearing
FAG	2319-K-M	d = 95	D = 200	B = 67	Self-aligning ball bearing
FAG	2319-K-M-C3	d = 95	D = 200	B = 67	Self-aligning ball bearing
FAG	2319-M	d = 95	D = 200	B = 67	Self-aligning ball bearing
FAG	2319-M-C3	d = 95	D = 200	B = 67	Self-aligning ball bearing
NSK	2319	d = 95	D = 200	B = 67	Self-aligning ball bearing
NSK	2319K	d = 95	D = 200	B = 67	Self-aligning ball bearing
SKF	2319 M	d = 95	D = 200	B = 67	Self-aligning ball bearing
FAG	1220-K-M-C3	d = 100	D = 180	B = 34	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
FAG	1220-M	d = 100	D = 180	B = 34	Self-aligning ball bearing
FAG	1220-M-C3	d = 100	D = 180	B = 34	Self-aligning ball bearing
NSK	1220	d = 100	D = 180	B = 34	Self-aligning ball bearing
NSK	1220K	d = 100	D = 180	B = 34	Self-aligning ball bearing
SKF	1220	d = 100	D = 180	B = 34	Self-aligning ball bearing
FAG	2220-K-M	d = 100	D = 180	B = 46	Self-aligning ball bearing
FAG	2220-K-M-C3	d = 100	D = 180	B = 46	Self-aligning ball bearing
FAG	2220-M	d = 100	D = 180	B = 46	Self-aligning ball bearing
FAG	2220-M-C3	d = 100	D = 180	B = 46	Self-aligning ball bearing
NSK	2220	d = 100	D = 180	B = 46	Self-aligning ball bearing
NSK	2220K	d = 100	D = 180	B = 46	Self-aligning ball bearing
SKF	2220	d = 100	D = 180	B = 46	Self-aligning ball bearing
SKF	2220 M	d = 100	D = 180	B = 46	Self-aligning ball bearing
FAG	1320-K-M-C3	d = 100	D = 215	B = 47	Self-aligning ball bearing
FAG	1320-M	d = 100	D = 215	B = 47	Self-aligning ball bearing
NSK	1320	d = 100	D = 215	B = 47	Self-aligning ball bearing
NSK	1320K	d = 100	D = 215	B = 47	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
SKF	1320	d = 100	D = 215	B = 47	Self-aligning ball bearing
FAG	2320-K-M-C3	d = 100	D = 215	B = 73	Self-aligning ball bearing
FAG	2320-M	d = 100	D = 215	B = 73	Self-aligning ball bearing
FAG	2320-M-C3	d = 100	D = 215	B = 73	Self-aligning ball bearing
NSK	2320	d = 100	D = 215	B = 73	Self-aligning ball bearing
NSK	2320K	d = 100	D = 215	B = 73	Self-aligning ball bearing
SKF	2320 M	d = 100	D = 215	B = 73	Self-aligning ball bearing
FAG	1221-M	d = 105	D = 190	B = 36	Self-aligning ball bearing
NSK	1221	d = 105	D = 190	B = 36	Self-aligning ball bearing
NSK	2221	d = 105	D = 190	B = 50	Self-aligning ball bearing
NSK	1321	d = 105	D = 225	B = 49	Self-aligning ball bearing
NSK	2321	d = 105	D = 225	B = 77	Self-aligning ball bearing
FAG	1222-K-M	d = 110	D = 200	B = 38	Self-aligning ball bearing
FAG	1222-K-M-C3	d = 110	D = 200	B = 38	Self-aligning ball bearing
FAG	1222-M	d = 110	D = 200	B = 38	Self-aligning ball bearing
FAG	1222-M-C3	d = 110	D = 200	B = 38	Self-aligning ball bearing
NSK	1222	d = 110	D = 200	B = 38	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
NSK	1222K	d = 110	D = 200	B = 38	Self-aligning ball bearing
SKF	1222	d = 110	D = 200	B = 38	Self-aligning ball bearing
FAG	2222-K-M	d = 110	D = 200	B = 53	Self-aligning ball bearing
FAG	2222-K-M-C3	d = 110	D = 200	B = 53	Self-aligning ball bearing
FAG	2222-M	d = 110	D = 200	B = 53	Self-aligning ball bearing
FAG	2222-M-C3	d = 110	D = 200	B = 53	Self-aligning ball bearing
NSK	2222	d = 110	D = 200	B = 53	Self-aligning ball bearing
NSK	2222K	d = 110	D = 200	B = 53	Self-aligning ball bearing
SKF	2222	d = 110	D = 200	B = 53	Self-aligning ball bearing
SKF	2222 M	d = 110	D = 200	B = 53	Self-aligning ball bearing
FAG	1322-K-M-C3	d = 110	D = 240	B = 50	Self-aligning ball bearing
FAG	1322-M	d = 110	D = 240	B = 50	Self-aligning ball bearing
NSK	1322	d = 110	D = 240	B = 50	Self-aligning ball bearing
NSK	1322K	d = 110	D = 240	B = 50	Self-aligning ball bearing
SKF	1322 M	d = 110	D = 240	B = 50	Self-aligning ball bearing
FAG	2322-K-M-C3	d = 110	D = 240	B = 80	Self-aligning ball bearing
FAG	2322-M	d = 110	D = 240	B = 80	Self-aligning ball bearing

Self-aligning ball bearings

Self-aligning ball bearings

d is the recorded bore; D is the recorded outside diameter. B is a ring/bearing width. Preserve any other axial symbol exactly as printed.

Brand	Complete designation	Inside (mm)	Outside (mm)	Axial (mm)	Recorded construction / configuration
FAG	2322-M-C3	d = 110	D = 240	B = 80	Self-aligning ball bearing
NSK	2322	d = 110	D = 240	B = 80	Self-aligning ball bearing
NSK	2322K	d = 110	D = 240	B = 80	Self-aligning ball bearing
FAG	1224-M	d = 120	D = 215	B = 42	Self-aligning ball bearing
FAG	1224-M-C3	d = 120	D = 215	B = 42	Self-aligning ball bearing
SKF	1224 M	d = 120	D = 215	B = 42	Self-aligning ball bearing
FAG	1226-M	d = 130	D = 230	B = 46	Self-aligning ball bearing
SKF	1226 M	d = 130	D = 230	B = 46	Self-aligning ball bearing
FAG	1228-M	d = 140	D = 250	B = 50	Self-aligning ball bearing
SKF	13030	d = 150	D = 225	B = 56	Large-size self-aligning ball bearing
FAG	1230-M	d = 150	D = 270	B = 54	Self-aligning ball bearing
SKF	13940	d = 200	D = 280	B = 60	Large-size self-aligning ball bearing
SKF	13944	d = 220	D = 300	B = 60	Large-size self-aligning ball bearing
SKF	13948	d = 240	D = 320	B = 60	Large-size self-aligning ball bearing